

Our HypotMAX<sup>®</sup> Series is a complete line of automated Hipot instruments designed to meet the demanding requirements of high voltage applications. We've included our patented SmartGFI® feature for maximum operator safety as well as a variety of advanced features to increase productivity on the production line and in the lab. Set up and run tests with confidence from our intuitive user interface or automate with a PC.

# AVAILABLE INTERFACES



## **SAFETY & PRODUCTIVITY FEATURES**



7710

DC WITHSTAND VOLTAGE TESTER

•





PLC Remote Basic PLC relay control

SmartGFI® Automatic operator shock protection

Remote Safety Interlock Easily disable HV output









Arc Detection High frequency filter for corona

Ramp-HI® Reduce ramp time during detection DC Hipot

Charge-LO<sup>®</sup> Confirms proper DUT connection



options

WithStand Automation Software

Accredited Cal Accredited calibration

available



Find the Model that Fits Your Testing Needs





Č



7705 7710

7715 7720

ASSOCIATED RESEARCH

HYPOT

# HypotMAX<sup>®</sup> Series

INPUT SPECIFICA				
Voltage	115/230 VAC ± 10%, Single Phase, User Selection			
Frequency	50/60 Hz ± 5%			
Fuse	6.3 A, 250 V Slow Blow			
DIELECTRIC WITH	HSTAND TEST MODE			
Output Rating	7705: 7710: 7715: 7720:	10 kV @ 20 mAAC 12 kV @ 10 mADC 20 kV @ 10 mAAC 20 kV @ 5 mADC		
HI-Limit and LO-Limit	7705	Range 1: Resolution: Range 2: Resolution:	0.0 – 9.999 mA 0.001 mA 10.00 – 20.00 mA 0.01 mA	
	7710	Range 1: Resolution: Range 2: Resolution:	0.00 – 999.9 μA 0.1 uA 1,000 – 9,999 μA 1 μA	
	7715	Range: Resolution:	0.00 – 9.999 mA 0.001 mA	
	7720	Range 1: Resolution: Range 2: Resolution:	0.0 – 999.9 μA 0.1 μA 1,000 – 5,000 μA 1 μA/step	
	77XX	Accuracy:	± (2% of setting + 2 counts)	
DC Ramp HI	7710	13 mA peak maximum, 10 mADC, ON/OFF selectable		
	7720	6.75 mA peak	maximum, 5 mADC, ON/OFF selectable	
DC Charge LO	7710/7720	Range:	0.0 – 350 µADC or auto set	
Arc Detection	7705	1 – 9 at output voltage < 7.00 kV 1 – 8 at output voltage ≥ 7.00 kV		
	7710/7720	1 – 9		
	7715	1 – 9 at output voltage < 15.00 kV 1 – 7 at output voltage ≥ 15.00 kV		
Voltage Display	7705	Range: Accuracy:	0.00 – 10.00 kV Full scale ± (2% of reading + 20 V)	
	7710	Range: Accuracy:	0.00 – 12.00 kV Full scale ± (2% of reading + 20 V)	
	7715/7720	Range: Accuracy:	0.00 – 20.00 kV Full scale ± (2% of reading + 20 V)	
Current Display	7705	Auto Range Range 1: Range 2:	0.000 – 3.500 mA 3.00 – 20.00 mA	
	7710	Auto Range Range 1: Range 2: Range 3:	0.0 – 350.0 μA 300 – 3500 μA 3,000 – 9,999 μA	
	7715	Auto Range Range 1: Range 2:	0.000 – 3.500 mA 3.00 – 10.00 mA	
	7720	Auto Range Range 1: Range 2:	0.0 – 350.0 μA 300 – 5,000 μA	
DC Output Ripple	7710	< 5% Ripple a	at 12 kV @ 9,999 µA, Resistive Load	
	7720 $< 5\%$ Ripple at 20 kV @ 4,999 $\mu A,$ Resistive Load			
AC Output Waveform	Sine Wave, Crest Factor = 1.3 – 1.5			
Output Frequency	Range: 50/60 Hz, User Selection ± (1% of output + 5 V) from Regulation No load to full load			
Output Regulation	± (1% of output + 10 V) from no load to full load			
Discharge Timer	7710 No load < 400 ms			
	7720	No load < 50	0 ms	
Dwell Timer	Range:   0, 0.3 - 999.9 sec (0=Continuous)     AC Range:   0, 0.3 - 999.9 sec or min (0=Continuous)     DC Range:   0, 0.4 - 999.9 sec or min (0=Continuous)			
Ramp Timer	7705/7715	Range:	0.3 – 999.9 sec	
	7710/7720	Range:	0.4 – 999.9 sec	
Ground Continuity	Max. Ground Resistance 1 $\Omega \pm 0.1 \Omega$ , fixed			

DIELECTRIC WITHSTAND TEST MODE				
Ground Fault Interrupt	HV Shut Down Speed < 1 ms GFI Trip Current 1 mA max			
GENERAL SPECIFICATIONS				
Memory	50 memories w/ 8 steps per memory			
Mechanical	Tilt-up front feet			
Interface	Standard: USB, RS-232 Optional: GPIB			
Dimensions (W x H x D)	16.93" x 5.24" x 15.75" (430 x 133 x 400 mm)			
Weight	7705: 63.3 lb (28.7kg)   7710: 63.1 lb (28.6kg)   7715: 59.4 lb (26.9kg)   7720: 61.6 lb (27.9 kg)			

Why We Use Counts Associated Research publishes some specifications using "counts" which allows us to provide a better indication of the instrument's capabilities across measurement ranges. A count refers to the lowest resolution of the display for a given measurement range. For example, if the resolution for voltage is 1V then 2 counts = 2 V.

### Specifications subject to change without notice.